

FIK-5865-3 / FIK-5865-4 LED Annunciators

The FIK-5865-3 and 5865-4 LED annunciators provide 30 programmable LEDs (15 red, 15 yellow) for maximum flexibility with the Fike FCP Series fire alarm control panels. The 5865-3 fits into a standard 3-gang electrical box, and the 5865-4 fits into a standard 4-gang electrical box.

The annunciators are covered by a semi-transparent label and a cover plate. Up to eight 5865 series annunciators can be used with the FACP. The FIK-5865-3 provides alarm and trouble annunciation for 15 zones, while the 5865-4 adds reset and silence input switches for even more versatility.

COMPATIBILITY

The FIK-5865 annunciators are compatible with the following Fike FCP series panels:

- FCP-2100 / FCP-2100ECS
- FCP-300 / FCP-300ECS
- FCP-75

FEATURES

- 30 programmable LED outputs (15 red and 15 yellow)
- Up to eight FIK-5865 annunciators can be used on one panel
- Fits to a standard 3 or 4 gang electrical boxes
- Comes with four semi-transparent labels that can be typed or printed on
- Dip-Switch addressable
- Connects to FACP SBUS
- Both modules are UL 864 listed and comply with NFPA 72
- 4-wire connection to the FACP SBUS

APPROVALS

- UL Listed
- CSFM
- FM Approved

For exact certification listings, please reference the respective agency website.



5865-3



5865-4

SPECIFICATIONS

Dimensions (LxHxD):	FIK-5865-3: 5.56" x 4.1" x 1.75" (14.1 x 10.4 x 4.45 cm)
	FIK-5865-4: 7.375" x 4.1" x 1.75" (18.73 x 10.4 x 4.45 cm)
Mounting:	FIK-5865-3: 3-gang electrical box
	FIK-5865-4: 4-gang electrical box
Operating Temperature:	32° - 120°F (0° - 49°C)
Humidity:	10% to 93% relative humidity (non-condensing)
Operating Voltage:	24 Vdc
Current:	35 mA (standby); 145 mA (alarm)

ORDERING INFORMATION

Part Number	Description
FIK-5865-3	LED Annunciator, Red
FIK-5865-4	LED Annunciator, Red