

# EXP™ SEALED LEAD ACID BATTERIES

## DESCRIPTION

The 12-volt, rechargeable, sealed lead acid batteries offered by Fike supply the required Standby and Alarm power to the EXP controller in case of AC power failure. The EXP panel can house up to 44AH batteries. The required battery size is determined based on battery calculations specific to each EXP system.



## SPECIFICATIONS

PART NUMBER	BATTERY DESCRIPTION				DIMENSIONS			APPROX. WEIGHT LB. (KG)
	NOMINAL VOLTAGE (V)	NOMINAL CAPACITY @ 20 HR. RATE (AH)	TYPE	Terminals	LENGTH IN. (MM)	WIDTH IN. (MM)	HEIGHT IN. (MM)	
F0293306	12	7	Sealed Lead-Acid	Spade	5.94 (150.88)	2.56 (65.02)	3.70 (93.98)	4.63 (2.10)
F0293307		12		Spade	5.93 (150.62)	3.91 (99.31)	3.71 (94.23)	7.43 (3.37)
F0293308		18		Spade	7.13 (181.10)	2.99 (75.95)	6.57 (166.88)	11.20 (5.08)
E10-0083-1		35		Nut & Bolt	7.76 (197.10)	5.16 (131.06)	6.26 (159.00)	22.11 (10.03)
E10-0083-3		44		Bolt	7.76 (197.10)	6.50 (165.10)	6.69 (169.93)	29.76 (13.50)

## ORDERING

PART NUMBER	DESCRIPTION	BRACKET REQUIRED (P/N) <sup>1</sup>
F0293306	12VDC, 7AH batteries (qty. 2)	F0292831
F0293307	12VDC, 12AH batteries (qty. 2)	F0292831
F0293308	12VDC, 18AH batteries (qty. 2)	F0292832
E10-0083-1	12VDC, 35AH batteries (qty. 2)	F0292831
E10-0083-3	12VDC, 44AH batteries (qty. 2)	F0292833

<sup>1</sup> Brackets are ordered separately.